


uSDX V1.02 PCB "Serial Resonance LPF Tri Band Module" Band dependent components list

Band	CX-1	CX-2	CX-3	CX-4	CX-5	CX-6	LX-1	LX-2	L1
80	680pf	360pf	1500pf	1800 pf	620pf	1800pf	21Turn/T37-2	15 Turn/T37-2	12Turn/FT37-43
60	430pf	620pf	620pf	1200pf	390pf	1200pf	17Turn/T37-2	12Turn/T37-2	
40	300pf	470pf	470pf	1000pf	300pf	1000pf	15Turn/T37-2	10Turn/T37-2	
30	200pf	330pf	330pf	680pf	220pf	680pf	12Turn/T37-2	8Turn/T37-2	
20	130pf	470pf		470pf	150pf	470pf	10Turn/T37-2	7Turn/T37-2	

X stands for Band slot. For example for band 1 components X = 1. For CX-1 it will be C1-1 which is the capacitor 1 of band 1

Same analogy goes for LX-1 and LX-2.



01

02

03

LPF 3